NPEXA-H511

single input, single output

Input: dry contact or proximity switch Output: relay

This isolated safety barrier converts switch or proximity detector signals (dry contact or NAMUR) from a hazardous area into relay signals to a safe area. The normal output sate and line fault detection function can be set with the DIP switch on the front side. The input, output, and power supply are galvanically isolated from each other.



Technical data

ff -

Power supply:	18 V DC~32 V DC (Reverse power protection)	
Power dissipation:	≤ 1.0W	
Input signal:	Dry contact or NAMUR	
Switching trigger point:	Input signal>2.1mA, signal "1",the yellow LED is	
	always bright	
	Input signal<1.2mA, signal "0", the yellow LED goes	
	out	
Open-circuit voltage:	Approx. 8.2V	
Short-circuit current:	Approx. 8mA	
output signal:	Relay contact	
Load capacity:	0.5A/35V DC	
LFD function:	When input current \leq 50µA, considers the input line	
	breakage, the output relay de-energized; If input	
	current \geq 6.5mA, considers the input circuit	
	short-circuit, the output relay de-energized, the red	
	LED flashing.	
Relay mechanical life:	>100000 switching cycles	
Switch frequency:	< 10Hz	
	d < 20ms	
Energized/De-energized	< 20ms	
Energized/De-energized delay:	< 20ms	
с с	< 20ms IEC 61326-3-1	
delay:		
delay: Electromagnetic		
delay: Electromagnetic compatibility:	IEC 61326-3-1	
delay: Electromagnetic compatibility:	IEC 61326-3-1 ≥ 2500 V AC (intrinsically safe side /	
delay: Electromagnetic compatibility:	IEC 61326-3-1 ≥ 2500 V AC (intrinsically safe side / non-intrinsically safe side)	
delay: Electromagnetic compatibility:	IEC 61326-3-1 ≥ 2500 V AC (intrinsically safe side / non-intrinsically safe side) ≥ 500 V AC (Power supply side /non-intrinsically	
delay: Electromagnetic compatibility: Dielectric strength:	IEC 61326-3-1 ≥ 2500 V AC (intrinsically safe side / non-intrinsically safe side) ≥ 500 V AC (Power supply side /non-intrinsically safe side)	
delay: Electromagnetic compatibility: Dielectric strength:	IEC 61326-3-1 ≥ 2500 V AC (intrinsically safe side / non-intrinsically safe side) ≥ 500 V AC (Power supply side /non-intrinsically safe side) ≥ 100 MΩ (Input /Output/Power supply)	

DIP switch settings

Switch State	а	b
S1	Normal mode	Inverted mode
S2	LFD on	LFD off

Wiring diagram



Explosive-proof parameters

National Supervision and Inspection Center for Explosion Protection and Safety of Instrumentation (NEPSI) Explosive-proof grade: [Ex ia Ga] II C Um: 250 V Certified parameters (Terminals 1, 2): Uo=10.5V, lo=11.3mA, Po=29.7mW II C : Co=0.97 μ F, Lo=100mH II B : Co=11 μ F, Lo=300mH II A : Co=52 μ F, Lo=700mH